

This Is An Original Product From Fulham Co., Inc.

LongHorse Series Versatile, Solid State Electronic Ballast. Small Case Size, High Power Factor, **Description:** 

Light Weight, Available In 120/277V 50/60Hz.

This Ballast Will Operate Following Lamps:



CFQ26W

## **ELECTRICAL DATA**

INPUT VOLT: 120V ± 10%, 50/60Hz									
LAMP WATTS/TYPE	LAMPS OPERATED	INPUT WATTS	LINE CURRENT	BALLAST FACTOR	EFFICACY FACTOR				
CFQ26W	4	88	0.79	0.8	0.9				
	///								
	10								
POWER FACTOR	> 0.9								
THD	< 34.6 %								
EMI/RFI COMPLIANCE	FCC PART 18-A								
SOUND RATING	"A"								
BALLAST TYPE	INSTANT START								
VOLTAGE TRANSIENTS	ANSI C82.11 - 1993								
INPUT/PROTECTION	FUSE								
OUTPUT/PROTECTION			-	,					
MIN. OPERATING TEMP	- 30°C ( - 20°F )								
MAX. CASE TEMP	70°C ( 158°F)								
ENERGY STAR 4.0									
APPROVALS/CLASS	UL /cUL LISTED, CLASS " P ", 1 OR 2 OUTDOOR								

## **MECHANICAL DATA**

WIRING DIAGRAMS										
WIRE	BLACK	WHITE	RED	BLUE	YELLOW	BROWN				
LENGTH-INCHES	12±1"	12±1"	24±1"	ı	24±1"	1				

**WIRING DIAGRAMS DEPEND** ON THE LAMP TYPE. PLEASE REFER TO FULHAM'S CATALOG.

Where: L = Length, W = Width, H = Height

NOTE: This Ballast Must Be Grounded.